

CORPORATE AND FRANCHISE DEVELOPMENT


UNDER THIS AGREEMENT, THE CONTRACTOR IS RESPONSIBLE FOR PURCHASE AND INSTALLATION OF THE SYSTEMS DESCRIBED IN THE PLANS. ALL COMPANY AND FRANCHISE PROJECTS SHALL CONTACT ACCUSEVE FOR A PRICE QUOTE AND A BILL OF MATERIAL CONFIRMATION FOR THEIR SPECIFIC PROJECT. SEE THE SWITCHGEAR SECTION IN THE SCOPE OF WORK FOR ADDITIONAL INFORMATION.

THE SWITCHGEAR PACKAGE CONSISTS OF SERVICE ENTRANCE SWITCHGEAR, MAIN PANELS, SUB PANELS, LIGHTING CONTACTORS AND ALL ASSOCIATED PRODUCTS TO COMPLIMENT THE SWITCHGEAR PACKAGE.












NOTE: THE SITE-ADAPT CONSULTANT IS RESPONSIBLE FOR DETERMINING IF THE SITE-SPECIFIC SWITCHGEAR PACKAGE FALLS WITHIN A JURISDICTION THAT REQUIRES EUSERC-COMPLIANT METERING EQUIPMENT.



EC SHALL VERIFY WITH LAHJ AND LOCAL UTILITY CONSTRUCTION GUIDELINES TO ENSURE FULL COMPLIANCE WITH ELECTRICAL SERVICE REQUIREMENTS. EC SHALL COORDINATE WITH LAHJ AND LOCAL UTILITY AND SHALL BE ASSURED OF LOCAL APPROVAL OF SERVICE DESIGN PRIOR TO PURCHASE OR INSTALLATION OF ANY SERVICE EQUIPMENT. CONTACT THE ENGINEER IMMEDIATELY WITH ANY PROBLEMS OR CHANGES. ANY COSTS ARISING FROM FAILURE TO FULLY COORDINATE SERVICE INSTALLATION AND COMPLY WITH LAHJ AND LOCAL UTILITY SHALL BE BORNE BY THE EC

E

B


	FUSIBLE DISCONNECT SWITCH WITH STARTER
	FUSED DISCONNECT SWITCH
	NON-FUSED DISCONNECT SWITCH
	PHOTOCELL
	RAIN SENSOR
	LED WALL MOUNT FIXTURE
	EMERGENCY LIGHT
	SINGLE POLE, SINGLE THROW TOGGLE SWITCH
	SINGLE POLE, SINGLE THROW TOGGLE SWITCH W/ PILOT LIGHT
	RELAY
	CONDUIT RUN, UNDERGROUND
	SMOKE DETECTOR
	EXTERIOR WALL FIXTURE
	EXTERIOR DECORATIVE WALL FIXTURE
	EXTERIOR DECORATIVE WALL FIXTURE
	WEATHERPROOF GROUND FAULT

F

D

- 1 WIRE ISOLATED GROUND TO ISOLATED GROUND BUS IN PANEL AND LAND ISOLATED GROUND TO SINGLE POINT GROUND. "DO NOT COMBINE COMMON GND TO ISOLATED GROUND".
- 2 BUILDING MAIN DISCONNECT FOR THIS SERVICE:
LABEL MAIN BREAKER AS INDICATED: (ENGRAVED LETTERS X 3/4" HIGH)
"MAIN SERVICE DISCONNECT "
- 3 EQUIPMENT PANEL IS PROVIDED BY EQUIPMENT VENDOR. EC SHALL INSTALL AS SHOWN.
- 4 PROVIDE 2" CONDUIT STUBBED INTO BUILDING FROM LATERAL POLE OR PEDESTAL FOR TELEPHONE.
- 5 VERIFY AVAILABLE FAULT CURRENT AT SERVICE ENTRANCE WITH THE UTILITY CO. TO CONFIRM 65 KA IC RATED EQUIPMENT IS SUFFICIENT.
- 6 5/8" DIA. x 10'-0" COPPER CLAD GROUND RODS. INSTALL AND CONNECT GROUND SYSTEM PER N.E.C ARTICLE 250.
- 7 INSTALL UNDERGROUND SERVICE LATERAL TO UTILITY TRANSFORMER PER SERVING UTILITY COMPANY SPECIFICATIONS. 4#350kcmil.CU. IN EACH OF (2) 3' C. TO PAD MOUNT TRANSFORMER, GC/ELECT. CONTRACTOR SHALL COORDINATE SERVICE POLES PER LOCAL UTILITY CODE. ALUMINUM CAN ONLY BE USED WITH SPECIFIC APPROVAL FROM THE OWNER.

C



TACO BELL
ROCKFISH RD. (NEAR BELSHAW WAY)
FAYETTEVILLE, NC 28306
"Stoney Point"



E2.0